

HP1506 Power Pack

● Characteristics

- Spare part of HA3000 Series
- Receive the control signal from HA3000 series products and drive the relay (five sets) on/off function
- Provide three DI points status signal back to HA3000 series products
- Power DC12V to electric lock
- If external battery connected, an external power supply to HA3000 series products and electric lock when AC power source failure
- Supply DC13.8V to HA3000 series items, battery recharge included
- Alarm relay activated when HA3000 series being removed (tamper) or malfunction
- Function of five relays
 1. Strike relay Control electric lock
 2. Alarm relay Emergency case
 3. Dress relay When anti-dress function activated
 4. Guard relay When arm/disarm activated by security password
 5. Patrol relay When patrol card or patrol password activated (Door bell function for HA3060)
- Three input point
 1. Exit button Input Egress purpose
 2. Door status input Door open / close detector
 3. Suspend status input All function halt (Emergency for HA3060)



● Specification

Model	HP1506
Power Input	AC 110V / 220V
Power Output	DC 12V 1.2A for strike DC 12v 300Ma for reader} DC 1.8V 350mA for battery charge
Control Relay	5 sets, 24V DC, 3A, NC/NO
Input(s)	3 sets
Case Material	Metallic
Dimension	60 (H) X 175 (W) X 120 (D) mm
Weight	3 kg
Working Voltage	DC 10~15Volt
Power Consumption	150mA Max.@12 VDC
Operating Temperature	0 ~50
Humidity	5%~95% (no condensation)